

S690P Rogowski Coil Power Meter



- 5 Test Modes - AC Current, Voltage, Frequency, Phase Angle, and Power
- Wide Measurement Range - 0.01A~9999A, 0.01V~1kV
45~65Hz, 0°~360°, 0.1mW~9999kW
- Versatile - Able to clamp around wires and cables of various sizes
- Data Hold & Data Save Function
- Easy to Use - Simply pull to disconnect the joint


DESCRIPTION

The coil of our Rogowski Coil Power Meter (Flexible Clamp Meter) is designed to be open and closed like a lid of a pen. Simply pull out of/push into the notch to disconnect/connect it, which is very easy to operate. It is designed to measure AC Current, Voltage, Frequency, Phase Angle, and Power. It is widely used in many industries, and is especially suitable for testing applications such as: wire systems of high density, transformer core grounding current, current of thick cables; power of motors and transformers; relays, thyristor-controlled rectifier, semiconductor switches, power electronic conversion equipment, and arc welding in industrial environments where current is severely distorted.

SPECIFICATIONS

Function	AC Current, Voltage, Frequency, Phase Angle & Power
Testing Method	Flexible CT, Integration
Power	3V DC (AAA 1.5V X 2)
Display	4-bit LCD display, backlight function, suitable for dark ambient
Measurement Range	Current: 0.00A ~ 9999A Voltage: 0.00V~1000V Frequency: 45~65Hz Phase Angle: 0°~360° Power: 0.0mW~9999kW
Accuracy (26°C ± 3°C, Below 70%RH)	Current: ±2%±3dgt Voltage: ±1.5%±3dgt Frequency: ±0.5Hz Phase Angle: ±3° Power: ±2%±3dgt
Resolution	10mA, 0.01V, 0.1Hz, 1°, 0.1mW
Clamp Size	Inner Diameter Φ200mm
Coil Spec	Thickness Φ7.5mm, length 650mm
Data Storage	99 Sets, blinking of the "FULL" symbol indicates that memory is full
Position of Conductor	Middle of the clamp/coil
USB Port	Data upload to a PC for better analysis
Frequency	50Hz and 60Hz, Auto detection
Range	Auto
Sampling Rate	2 Samples/second
Line Voltage	Below AC 1000V
Dimensions	Instrument: 350mm×220mm×38mm (Coil expanded) Package: 285mm×175mm×63mm

Data Hold	Data hold function is indicated by the "DH" symbol
View Data	Press and hold the MEM button to view data
Overload	Overload is indicated by the "OL" symbol
Peak Hold	Capture and hold the highest magnitude of the measured parameter
Auto Shutdown	The instrument will be shut down after 15 minutes of idle
Low Battery	Please replace the batteries when the battery voltage is low
Weight	300g (with batteries), 750g (package)
Operating Current	30mA
Ideal Working Conditions	-10 C ~ 40 C , below 80%RH
Ideal Storage Conditions	-10 C ~ 60 C , below 70%RH
Safety Standards	IEC1010-1, IEC1010-2-032, Pollution Category II, CAT III (600V)

ACCESSORIES & ORDER DATA			
Description	Order Code	Description	Order Code
Rogowski Coil Power Meter	S690P	Included accessories for S690P	
		Instrument, 1 pc	
		Instrument Bag, 1 pc	
		Voltage Test Leads, 2 pcs	
		USB Cable, 1 pc	
		Batteries (AAA 1.5V), 2 pcs	
		Manual and Certificate of Conformity, 1 of Each	

SALES OFFICE

Email: sales@eaglotest.com

Tel: (852) 2947 1888

Add: 11F/, Long To Building, 654-656 Castle Peak Road,
Lai Chi Kok, Kowloon, Hong Kong.

S690P

Rogowski Coil Power Meter

www.eaglotest.com

Eaglotest Technology | Precision & Accuracy